


ITEM #	PART #	QTY	DESCRIPTION	
1	0L2910	1	XFRSW HSB 100A 2P 250V	
2	074908	6	SCREW HHTT M5-0.8 X 10 BP	
3	077033	6	LUG SLDLSS 1/0-#14X9/16 AL/CU	
4	0G7624	6	SCREW PPHM #10-32 X 5/16	
5	022152	6	WASHER LOCK SPRING #10 ZC	
6	G074138	1	LUG DIS QK N1-S 10X45 DEG BR/T	
7	10000009445	4	90 DEGREE STRAIGHT SPADE CONNECTOR	
8	0E7886H	1	CB 0100A 2P 240V S BQ2 LB	
9	0E7890	1	BRKT CB MTG BACK	
10	0G5780A	1	ASSY WIRE 2AWG 5.375" #N1A BLK	
11	0G5780B	1	ASSY WIRE 2AWG 6.875" #N2A BLK	
12	0A1495	4	SCREW HHTT M4-0.7 X 10 BP	
13	0K0108	1	ASSY-NEUT BLK 100A	
14	090388	2	SCREW HHTT M6-1.0 X 12 ZINC	
15	026902	1	SCREW HHTT #8-32 X 1/4 CZ	
**	16	0K01120ALOR	1	ENCLOSURE 100/200A XFER SW_RAW
**	17	0K01130ALOR	1	COVER 100A XFER SWITCH_INST_RAW
**	18	10000014617	1	SUBPLATE 100/200A XFER SW
**	19	0K11120ALOR	1	COVER INSIDE 100A SE GRAY_RAW
**	20	0K1119	1	RISER 100A SERV ENT
*	21	0K1098	1	DECAL RTS TRANSFER SW GENERAC
	22	0L1950A	1	DATA DECAL TSWS SE
	23	0E3484	1	DECAL WARN MANUAL OPER HANDLE
	24	0F9969	1	DECAL UTILITY DISCONNECT
	25	0K1018	1	DECAL, NEUTRAL CONNECTION
	26	0K1738	1	DECAL TEST SEQUENCE 100-200A SE
	27	0H7274	1	DECAL NEC COMPLIANCE
	28	0G3259	1	DECAL TERMINAL SHOCK HZD B1
	29	0G3274	1	DECAL LIVE CIRCUIT ENG/FRN/SPN
	30	0K1167	1	WIRE NEUTRAL TO GROUND CONNECTION
	31	0J8202	1	LUG SLDLSS 2/0-#14X#10-32X.125
	32	026850	2	WASHER LOCK EXT 1/4 STL
**	33	0G8411	6	NUT HEX FLANGE WHIZ 1/4-20
**	34	085889	1	NUT HEX 1/4-20 SS
**	35	022473	4	WASHER FLAT 1/4-M6 STEEL ZINC
	36	0K8254	1	U-CLIP ADHESIVE
	37	0E6155	1	PIN ARM EXTENDER
	38	10000004183	1	ASSY SMART AC MODULE
	39	10000005872	1	HARNESS 100/200A TS
	40	10000008602	1	DECAL WCR NEC COMPLIANCE
	41	10000005117	1	FUSE 6.3A 250VAC 5mmX20mm
	42	0L6700	1	SCREW THUMB 1/4-20 X 1/2 KNURL

-FRONT DECAL PER MODEL
 **COMPONENTS INCLUDED WITH KIT • 10000014649 LISTED BELOW:

- 0K01120AL14 - ENCLOSURE 100/200A XFER SW - QTY 1
- 0K01130AL14 - COVER 100A XFER SWITCH - QTY 1
- 10000014617 - SUBPLATE, 100/200A XFER SW - QTY 1
- 0K11120AL14 - COVER INSIDE 100A SE GRAY
- 0K1119 - RISER 100A SERV ENT
- 0G8411 - NUT HEX FL WHIZ 1/4-20 - QTY 4
- 022473 - WASHER FLAT 1/4-M6 ZINC - QTY 4

36 37 SUGGESTED LOCATION OF U-CLIP AND ARM EXT PIN TO BE INCLUDED IN MANUAL BAG



SECTION D-D

PART NUMBER	DESCRIPTION	ITEM #	MODEL #	MANUAL	WARRANTY
10000008162	ASSEMBLY 100A 120/240 SE	0K1098	RXSW100A3	10000009569	0K9470
10000008134	ASSEMBLY 100A 120/240 SE	0K1274	RXSM100A3	10000009532	0K3103
10000008162	ASSEMBLY 100A 120/240 SE	0K1272	RXSW100A3S	10000009569	0K3106

REFERENCE DRAWINGS
 10000008038 SCHEMATIC/WIRING DIAGRAMS
 0F6778 CARTON 305 X 14.2 X 78
 10000014649 KIT ENCL 100 SE AL

GENERAL TOLERANCES UNLESS NOTED	
ALL XX	± 0.4 MM
XXX	± 0.4 MM
XXXX	± 0.5 MM
ALL ANG	± 1°
INTERPRET DIM AND TOL PER ASME Y14.5M-1994	



TITLE
GENERAL
 ASSEMBLY DWG 2-POLE
 100A 120/240V SE

ISSUE DATE:
 SIZE D CAGE NO N/A DWG NO 10000008170 REV B
 SCALE 0.400 WT-KG 85441.576 SHEET 1 of 1

GENERAL ASSEMBLY DRAWING

